

Axygen® Gel Documentation System and Axygen Gel Documentation System-BL

User Manual

AXYGEN®

A Corning Brand



Safety and Regulatory Compliance

Important Safety Information

Please read these instructions before operating the Axygen® Gel Documentation System (GD-1000) and Axygen Gel Documentation System-BL (GDBL-1000).

UV Safety Precautions



CAUTION

Because ultraviolet (UV) radiation can cause serious damage to unprotected eyes and skin, we recommend wearing UV glasses or a face shield.

The Axygen Gel Documentation systems come with a built-in ultraviolet (UV 200 to 400 nm) transilluminator inside the system. Exposure to UV radiation can cause permanent damage to the eyes and skin. The system enclosure confines the radiation within the system and shields the user from exposure. The system is also equipped with a two-way safety interlock switch that automatically cuts off the power to the transilluminator when the door is open during normal use.

- ▶ Always wear UV-protective eyewear that is specified by the manufacturer as providing protection at the wavelength(s) used, making sure that the eyewear protects any areas where radiation may come through (UV sunglasses may not prevent UV radiation from coming in through the sides or around the lenses).
- ▶ Always cover all skin that may be exposed to UV light, especially the face, neck, hands, and arms.
- ▶ Always make sure that any UV protection devices (such as the safety switch on the light cabinet apparatus) are working properly. If not, discontinue use until the device(s) are properly repaired.
- ▶ Use only UV lamps in the transilluminator.

Electrical Safety Precautions

Be sure to take proper precautions when handling any electrical equipment. NEVER work on any live circuit, fixture, receptacle, or switch. Safety rules you should follow whenever working with any electrical appliance include:

- ▶ Always shut off power at the main disconnect before changing a fuse.
- ▶ Always shut off power to the circuit before repairing or replacing a switch, receptacle, or fixture.
- ▶ Always tape over the main switch, empty fuse socket, or circuit breaker you are working on.
- ▶ Always check that the circuit is dead before beginning work on it. Using a circuit tester or voltmeter can help you determine this.
- ▶ Always unplug any appliance before repairing it.



Protective Earth Terminal

The earth terminal, intended for connection to an external protective conductor for protection against electric shock in case of a fault, is located on the inside of the back panel.



Hot Surface Warning

Under normal conditions, the temperature of glass surface of UV transilluminator is below 50°C and safe to touch. However, if the system malfunctions, it is possible that the glass surface temperature exceeds 80°C. Please exercise caution when touch the glass surface with your hand when this occurs.

For General Laboratory Use Only

This instrument is suitable for general laboratory use only. Therefore, it must be used only by personnel who know the health risks associated with the reagents that are normally used with this instrument.

Voltage Setting Information

The Axygen® Gel Documentation systems have a power supply that automatically chooses the correct voltage for your country or region.

Protection category: IP20 according IEC 60529

Table of Contents

1. Introduction	3
2. Specifications	4
3. System Placement	5
4. Axygen Gel Documentation System Installation Guide	6
5. Axygen Gel Documentation System-BL Installation Guide	8
6. Image Acquisition	9
7. Overview of Software Features	10
8. Optional Accessories	13
9. Copyright and Trademark Information	14
10. Warranty	15
11. Waste Electrical and Electronic Equipment (WEEE) Directive	16

1. Introduction

Congratulations on purchasing your Axygen® Gel Documentation System or Axygen Gel Documentation System-BL. The systems easily capture publication quality, 16 bit TIFF images. The systems are simple to set up and have a straightforward user interface for image capture, annotation, and contrast adjustment. Images are easily saved and opened in common gel analysis software for more detailed analysis.

The Axygen Gel Documentation System includes the following components:

- ▶ Axygen Gel Documentation system cabinet, including the camera and orange filter
- ▶ A-to-A male USB cable
- ▶ Quick Installation Guide and Quick Imaging Guide
- ▶ Axygen test target
- ▶ Axygen USB (includes imaging software, calibration files)
- ▶ 3-power cable 110V/220V (US/EU/UK). Please select the correct one for your region.

The Axygen Gel Documentation System-BL includes the following components:

- ▶ Axygen Gel Documentation System-BL cabinet, including the camera and orange filter
- ▶ Tablet computer (includes imaging software, calibration files)
- ▶ Quick Installation Guide and Quick Imaging Guide
- ▶ Axygen test target
- ▶ 3-power cable 110V/220V (US/EU/UK). Please select the correct one for your region.

2. Specifications

Axygen® System	Gel Documentation System	Gel Documentation System-BL
Camera	5.4 MP image resolution	5.4 MP image resolution
Lens	F1.8	F1.8
Light Sources	<ul style="list-style-type: none"> ▶ Epi White ▶ Dual wavelength transillumination at 302 nm and 365 nm 	<ul style="list-style-type: none"> ▶ Epi White ▶ Dual wavelength transillumination at 302 nm and 365 nm ▶ Epi Blue
Trans White Light Illumination Tray	Optional	Optional
Field of View	15 x 20 cm	15 x 20 cm
Cabinet	<ul style="list-style-type: none"> ▶ Door sensor to prevent accidental exposure to UV; automatically shuts off UV light when door is open ▶ Safety override, enabling band cutting on the UV transilluminator with automatic turn off after 5 minutes 	<ul style="list-style-type: none"> ▶ Door sensor to prevent accidental exposure to UV; automatically shuts off UV light when door is open ▶ Safety override, enabling band cutting on the UV transilluminator with automatic turn off after 5 minutes
Emission Filter	590 nm	590 nm
3-position Filter Slider	No	Yes
Certifications	CE, cTUVus	CE, cTUVus
Product Footprint	12" x 15" (30.48 x 38.1 cm)	12" x 15" (30.48 x 38.1 cm)
Computer	<ul style="list-style-type: none"> ▶ Operating system: Microsoft® Windows® 7 and above ▶ Minimum hardware requirements: 1.4 GHz processor speed, 2 GB RAM, 16 GB free hard disk space, 2 USBs 	<p>Tablet included: Windows 8 tablet computer enables compatibility with existing networks, as well as easy setup (also Windows 10 compatible)</p> <ul style="list-style-type: none"> ▶ Bluetooth and wireless compatible, or USB to LAN compatible ▶ 10.1" touch screen ▶ 2 GB of storage for short term data saving

3. System Placement

Please make sure the system is located away from regular exposure to water, solvents, or corrosive material. Place on a flat and stable surface with 10 cm clearance on all sides, including the top, to allow sufficient air flow.

The system is intended for indoor use with the following ambient conditions:

- a. Altitude up to 2,000 m
- b. Temperature 5°C to 40°C
- c. Maximum relative humidity 80% for temperatures up to 31°C decreasing linearly to 50% relative humidity at 40°C

The system should be placed away from interfering electrical signals and magnetic fields. If possible, a dedicated electrical outlet should be used to eliminate electrical interference from other instrumentation in your laboratory.

4. Axygen® Gel Documentation System Installation Guide

1.




Remove the Axygen Gel Documentation system from its packaging.

2.



Identify the Axygen USB and connect it to a Microsoft® Windows® 7 or 8 computer.


3.



On the USB, find the folder “Axygen Imaging Files\Axygen GDS_v_XXX” and open it. Double click on the **Setup** file.


(You may see a message pop up that says “Do you want to allow the following program from an unknown publisher to make changes to this computer?” Select **Yes**.)

4.




Click **Next** to begin the Setup Wizard.

5.




Select **GD1000**, then click **Next**.

6.




To continue, accept the license agreement. Then click **Next**.

7.




Select your installation location, then click **Next**.

8.




Click **Install** to continue with the installation.

9.




Click **Next** to begin the driver installation.

10.




To continue, accept the license agreement. Then click **Next**.

11.



After the installation is complete, click **Finish**.

12.



Click **Finish** to exit the Setup Wizard.

4. Axygen® Gel Documentation System Installation Guide (continued)

13.



On the Axygen USB, locate the folder “Axygen Imaging Files\ System Calibration Folder AXXXXX.”

14.

Find the “Master” folder within the “System Calibration Folder.” Copy the Master folder, and paste it in C:\ProgramData\Axygen\ Axygen Imaging.

When asked if you would like to replace the existing folder, select **Yes**.

*Note: if you cannot see the Program Data folder, please make sure you can view “hidden” files in Windows®.

15.



Plug the system into an available outlet.

16.



Connect the A-to-A USB cable to both the system USB and the computer. **On the Axygen system, ensure the USB is plugged into the lower USB on the right hand side of the instrument.**

17.



Power on the Axygen Gel Documentation system using the switch in the back. Wait about 20 seconds before proceeding to the next step.

18.



Launch the capture software.

19.



The first time you run the Axygen Capture Software, you will receive the message above. Click **Allow Access**.

5. Axygen® Gel Documentation System-BL Installation Guide

1.



Remove the Axygen Gel Documentation system-BL from its packaging.

2.



Locate the tablet computer.

3.



Remove the wing nuts from the back of the tablet.

4.



Mount the tablet on the system.

5.



Secure the tablet in place with the wing nuts.

6.



Connect the mini-USB cable to the tablet.

7.



Connect the power cable to the tablet.

8.




Plug the system into an available outlet.

9.



Power on the system using the switch on the back.

10.



Power on the tablet.

11.



Launch the capture software.

6. Image Acquisition

1. After the acquisition software is launched, select the **Darkroom** tab.
2. Place your sample in the imager. The capture software will be in “Live” mode to allow you to position your sample.
3. Close the cabinet door.
4. Select your light source.

Here is a quick guide to select your light source:

Axygen® System	Gel Documentation System	Gel Documentation System-BL
EtBr Gel	UV 302 or 365	UV 302 or 365
Sybr Safe Gel	UV 302	Epi Blue
Coomassie Gel*	Visible	Visible

*Requires optional white light tray

5. Select exposure time. If you are not sure of your exposure time, select **Auto Exposure**. Otherwise, you can select a time using the exposure slider.
6. A preview of your image will be displayed. If the image is acceptable, select **Image Capture**. Otherwise you can continue to modify the exposure time.
7. When you are done, your image will be displayed in the home tab. You can now save your image.

7. Overview of Software Features

Home Tab



Open

Open a previously saved image.



Save

Save allows you to perform one of three actions:

- ▶ Save – save the currently active image
- ▶ Save as – allows you to save the currently active image under another file name
- ▶ Save all – saves all open images




Print

Print active image.




Email

Allows you to email the active image. Please see “Email Settings” in the Settings section of this guide.



Resize

An image can be resized up to 3 times its original size.



Crop

When you select the crop tool, a crop window will appear over your image. Drag the corners of the crop window to your desired size, and then select “Crop ROI” from the bottom of the screen. If you do not want to crop, select “Cancel.”



Rotate

Rotate allows you to rotate your image one of four ways:

- ▶ Right 90 degrees
- ▶ Left 90 degrees
- ▶ Flip horizontal
- ▶ Flip vertical




Image Info

Captures some of the information on how your image was captured, including the date and time captured, and exposure time. Additionally, it tells you the light source and calibration value.



Zoom In

Zoom in on center of image




Zoom Out

Zoom out from center of image




Zoom Fit

Adjusts zoom to fill window. Displays % in the lower left corner of the window.




Auto Contrast

Calculates a balanced contrast ratio.




Manual Contrast

Allows you to manually adjust the black and white levels of your image.



Invert

Gives the inverse of the image.



Display Saturation

Saturated pixels are displayed in red.

7. Overview of Software Features (continued)

Darkroom Tab



UV 302

Selects the Trans UV 302 light source.



UV 365

Select the Trans UV 365 light source.



Epi White

Selects the Epi White light source.



Epi Blue

Turns on the Epi Blue light source.
Axygen Gel Documentation System–BL only




Trans White

Optional – with the purchase and calibration of the white light tray. You select the Trans White light source.




Slider

Use this slider to select your exposure time. As you change the time, wait for the live image below to update for the best experience. Alternatively, you can type in the exposure time in the text fields to the right, and then select **Enter**.




Auto Exposure

Calculates an exposure time using the full dynamic range of the camera.



Show Grid

Displays a grid over the live image so you can make sure your gel is vertically and horizontally straight.



Select ROI

Select ROI has two functions:

- ▶ Select ROI then select **Image Capture** – this results in a final cropped imaged
- ▶ Select ROI then select **Auto Exposure** – this results in auto exposure calculations only influenced by your region of interest.





Image Capture

Select this to capture your image. It will be displayed in the Home tab for further work.



Band Excision

If you need to open the door and view your gel with the lights on, you can override the safety precautions in our system.

NOTE: Always wear protective eyewear when dealing with UV light. To use the band excision tool, select your light source then select band excision. A dialog box will appear and ask you to pull out the safety switch on the right side of the system. Open the door, pull the safety switch, and the light will go on. Select “Band Excision” again to turn the light off. The light will automatically turn off after 5 minutes.

7. Overview of Software Features (continued)

Annotations Tab

The annotations tab lets you annotate or draw on an open image.



Pointer

This is the object selector. It allows selection of text boxes, objects, lines, etc., in order to edit or delete them. For example, to change the color of a box, select the pointer, double click on the box to be changed, then select the color select tool and click on the color desired.



Rectangle

Draw a rectangle on the image



Ellipse

Draw an ellipse on the image



Line

Draw a line on the image



Text

Click on the text box, then draw a rectangle. This rectangle will be where your text appears. You can change the size of the font after you type your text.



Pencil

Use this to free-hand draw on the image.



Undo

Use this tool to undo your last few steps.



Redo

Redo your last step.



Delete

Delete the highlighted annotation object.



Font/Color/Line Width

Once an annotation object is selected using the pointer, you can edit the line width and the color, and in the case of text, the font.

Settings Tab

The password for settings is **admin**.



Email Settings

You can email files to yourself if you set up an email account for the imaging system. Contact your IT department for the best values to set.



Create Flats

This tool is used to create flat field image for certain light sources. Flat files are used to calibrate light sources for the most even illumination. Flat field calibration is required if you purchase the White Light Tray accessory. Instructions for calibration and use are included with the tray.



Change Password

The default system password is **admin** (all lowercase). If you would like to change this password, you can do so here.



Enable Trans White

When optional White Light Tray is purchased, enables Trans White to appear as an option in the darkroom.

Help Tab

Allows you to view this user manual, save it, or print it.

8. Optional Accessories

Corning Cat. No.	Description
GD-1000	Gel Documentation System
GDBL-1000	Gel Documentation System-BL
GD-BLCS	Gel Documentation System blue light conversion screen for GD-1000
GD-WLCS	Gel Documentation System white light conversion screen for GD-1000 and GDBL-1000
GD-GCT	Gel carrying tray for GD-1000 and GDBL-1000
GD-PRT	Thermal printer
GD-PAPER	Thermal printer paper
GD-1D	1 user license of Total Lab 1D (also available in more user licenses upon request)
GD-1DN	1 user Network license of Total Lab 1D (also available in more user licenses upon request)
GDBL-BLUE	Optional blue filter (497 nm)
GDBL-GREEN	Optional green filter (572 nm)
GDBL-RED	Optional red filter (676 nm)
GD-GCS	UV transmitting tray that protects UV transilluminator when cutting out bands
GD-OG	Orange glasses ideal for reducing background when cutting out bands with blue light
GD-USBS	USB hub
GD-USBMK	USB mouse and keyboard

9. Copyright and Trademark Information

All goods and services are sold subject to the terms and conditions of sale of the company that supplies them. The company reserves the right, subject to any regulatory and contractual approval, if required, to make changes in specifications and features shown herein, or discontinue the product described at any time without notice or obligation.

Corning Incorporated
Life Sciences

836 North St.
Building 300, Suite 3401
Tewksbury, MA 01876
t 800.492.1110
t 978.442.2200
f 978.442.2476

www.corning.com/lifesciences

For more specific information on claims, visit the Certificates page at www.corning.com/lifesciences.

Warranty/Disclaimer: Unless otherwise specified, all products are for research use only. Not intended for use in diagnostic or therapeutic procedures. Corning Life Sciences makes no claims regarding the performance of these products for clinical or diagnostic applications.

10. Warranty

The Axygen® products are warranted against defects in materials and workmanship for two years unless otherwise outlined on your sales order. If any defect occurs in the instrument during this warranty period, Corning will repair or replace the defective parts at its discretion without charge. However, the following defects are specifically excluded:

- ▶ Defects caused by improper operation.
- ▶ Repair or modification done by anyone other than Corning or an authorized Corning agent
- ▶ Use of spare parts supplied by anyone other than Corning
- ▶ Damage caused by accident or misuse
- ▶ Damage caused by disaster
- ▶ Corrosion caused by improper solvents or samples

11. Waste Electrical and Electronic Equipment (WEEE) Directive



GD-1000 and GDBL-1000

Product Disposal Information For Corning Customers And Recyclers

According to Directive 2012/19/EU of the European Parliament and Council of 4th July 2012 on waste and electronic equipment (WEEE) as amended, the Axygen Gel Documentation System and Axygen Gel Documentation System-BL are marked with the crossed-out wheeled bin and must not be disposed of with domestic waste.

Consequently, the buyer shall follow the instructions for reuse and recycling of waste electronic and electrical equipment (WEEE) provided with the products and available at the following link: www.corning.com/weee.

GDBL-1000

The crossed out wheeled bin symbol is printed in the product instruction manual and on the packaging to indicate that, in accordance with the requirements of Directive 2006/66/EC of 6 September 2006 on batteries and accumulators and waste batteries and accumulators, batteries must be disposed of in accordance with national regulations.

Beginning-to-end
Solutions for

Cell Culture
Drug Discovery
Genomics
Microbiology
Chemistry

www.corning.com/lifesciences/solutions

At Corning, we continuously strive towards improving efficiencies and developing new products and technologies for life science researchers. We have scientists working in Corning R&D labs across the globe, doing what you do every day. Our technical experts understand your challenges and your increased need for high-quality products.

It is this expertise, plus a 160-year legacy of Corning innovation and manufacturing excellence, that puts us in a unique position to be able to offer a beginning-to-end portfolio of high-quality, reliable life sciences consumables.

For additional product or technical information, visit www.corning.com/lifesciences or call 800.492.1110. Outside the United States, call +1.978.442.2200 or contact your local Corning sales office.

Corning Incorporated
Life Sciences

836 North St.
Building 300, Suite 3401
Tewksbury, MA 01876
t 800.492.1110
t 978.442.2200
f 978.442.2476

www.corning.com/lifesciences

**Worldwide
Support Offices**

ASIA/PACIFIC

Australia/New Zealand
t 61 427286832

China
t 86 21 3338 4338
f 86 21 3338 4300

India
t 91 124 4604000
f 91 124 4604099

Japan

t 81 3-3586 1996
f 81 3-3586 1291

Korea

t 82 2-796-9500
f 82 2-796-9300

Singapore

t 65 6572-9740
f 65 6861-2913

Taiwan

t 886 2-2716-0338
f 886 2-2516-7500

EUROPE

France

t 0800 916 882
f 0800 918 636

Germany

t 0800 101 1153
f 0800 101 2427

The Netherlands

t 31 20 655 79 28
f 31 20 659 76 73

United Kingdom

t 0800 376 8660
f 0800 279 1117

**All Other European
Countries**

t 31 (0) 20 659 60 51
f 31 (0) 20 659 76 73

LATIN AMERICA
grupoLA@corning.com

Brasil

t (55-11) 3089-7400

Mexico

t (52-81) 8158-8400

CORNING | **FALCON** | **AXYGEN** | **GOSELIN** | **PYREX**

For a listing of trademarks, visit www.corning.com/clstrademarks.
All other trademarks are the property of their respective owners.